

# Smart A60 LFD BULB

**Product Mode: EX000245** 



11115	N	Pac

◆ Product Dimension 60\*60\*108mm

◆ Net Weight 35g

## **Mechanical Specification**

♦ Material Plastic+Aluminum

◆ Ingress Protection(IP)
IP20

## **Electrical Specification**

◆ Wattage 8.5W

♦ Input Voltage 220-240V 50/60Hz

◆ Equiv Wattage◆ Standby Power◆ Protocol60W0.5W◆ WIFI+BLE

♦ Net Standard 2.4G WiFi IEEE 802.11 b/g/n

♦ Lifetime 20,000hrs

◆ Connection Range (open area) 30m(Within WIFI signal)

 ◆ Cap
 B22

 ◆ Lumen
 850lm

◆ Colors RGB+2700-6500K

◆ CRI 80

◆ Compatibility Amazon Echo, Google Home

### **Software Function**

◆ CCT dimming	YES
◆ RGB dimming	YES
◆ Scenes	YES
◆ Music Sync	YES
◆ Plan	YES
◆ Schedule	YES
◆ Biorthythm	YES
♠ Power-on behavior	VEC

#### Operation

- 1. Download Tuya Smart APP -You can search "Tuya Smart" in either APP Store or Google Play to install the APP.
- 2. Register a Tuya Smart account and sign in the app You will be prompted to enter your mobile number or email address to register. The system automatically recognises your country / area. You can also select your country code.
- 3. When power on, the smart device will flash rapidly, then add relevant smart device to Tuya Smart App -Tap the icon+on the corner or "My device" page, choose your device type-Smart lighing, then follow the instructions in the App to connect the lamp. If not flashing rapidly, the smart device needs to be turned on/off/on/off/on/off/on, totally three times.
- 4. Enter Wi-Fi password, then connect. Make sure your router, mobile and lamp are as close as possible.
- 5. After connection, the lamp will appear in your list and you can control it from anywhere in the world. You can also rename the lamp and group more lamps.